

Mixers

Analogue Mixers

MXR-160

Order No. 0200150



16-channel audio mixer, with DSP effect unit, integrated MP3 player and Bluetooth receiver.

- Integrated USB audio interface (will be identified and addressed as an external sound card)
- Full-duplex USB port (allows for simultaneous recording and reproduction) for reproduction of digital audio data from a PC and for recording mixings onto a PC
- 14 mono input channels with gain control, 3-way equalizer and pan pot
- 1 stereo input channel with 3-way equalizer and balance control
- MP3 player
- USB interface
- Bluetooth receiver
- DSP delay, adjustable
- Adjustable aux return input and FX send output
- Tape record/play connections
- 5-band stereo graphic equalizer
- +48 V phantom power, can be activated as required
- Pre-fader listening (PFL) to the stereo input channels via adjustable headphone output
- Stereo LED level display



| Model | MXR-160 |
|--------------------|---|
| Mic input | 2.2 mV, bal. 14 x XLR |
| Line input | 50 mV (stereo), 1 x 6.3 mm jack L/R 30 mV (mono), 14 x 6.3 mm jack |
| Tape (play) | 290 mV, 1 x RCA L/R |
| Aux input | 420 mV, 1 x 6.3 mm jack L/R |
| Master output | 880 mV, bal. 1 x XLR L/R 880 mV, 1 x 6.3 mm jack L/R |
| Effect send | 9 V, 1 x 6.3 mm jack |
| Tape (rec) | 400 mV, 1 x RCA L/R |
| Headphones | ≥ 8 Ω, 1 x 6.3 mm jack |
| Frequency range | 20-20,000 Hz |
| THD | < 0.03% |
| S/N ratio | > 82 dBA |
| Equalizer bass | ±15 dB/80 Hz |
| Equalizer midrange | ±15 dB/2.5 kHz |
| Equalizer treble | ±15 dB/12 kHz |
| Power supply | ~ 230 V/50 Hz/35 VA |
| Dimensions | 614 x 53 x 340 mm |
| Weight | 5.4 kg |

MXR-120

Order No. 0200100



12-channel audio mixer, with DSP effect unit, integrated MP3 player and Bluetooth receiver.

- Integrated USB audio interface (will be identified and addressed as an external sound card)
- Full-duplex USB port (allows for simultaneous recording and reproduction) for reproduction of digital audio data from a PC and for recording mixings onto a PC
- 10 mono input channels with gain control, 3-way equalizer and pan pot
- 1 stereo input channel with 3-way equalizer and balance control
- MP3 player
- USB interface
- Bluetooth receiver
- DSP delay, adjustable
- Adjustable aux return input and FX send output
- Tape record/play connections
- 5-band stereo graphic equalizer
- +48 V phantom power, can be activated as required
- Pre-fader listening (PFL) to the stereo input channels via adjustable headphone output
- Stereo LED level display



| Model | MXR-120 |
|--------------------|---|
| Mic input | 2.2 mV, bal. 10 x XLR |
| Line input | 50 mV (stereo), 1 x 6.3 mm jack L/R 30 mV (mono), 10 x 6.3 mm jack |
| Tape (play) | 290 mV, 1 x RCA L/R |
| Aux input | 420 mV, 1 x 6.3 mm jack L/R |
| Master output | 880 mV, bal. 1 x XLR L/R 880 mV, 1 x 6.3 mm jack L/R |
| Effect send | 9 V, 1 x 6.3 mm jack |
| Tape (rec) | 400 mV, 1 x RCA L/R |
| Headphones | ≥ 8 Ω, 1 x 6.3 mm jack |
| Frequency range | 20-20,000 Hz |
| THD | < 0.03% |
| S/N ratio | > 82 dBA |
| Equalizer bass | ±15 dB/80 Hz |
| Equalizer midrange | ±15 dB/2.5 kHz |
| Equalizer treble | ±15 dB/12 kHz |
| Power supply | ~ 230 V/50 Hz/30 VA |
| Dimensions | 498 x 53 x 340 mm |
| Weight | 4.4 kg |