

Mixers

Analogue Mixers

MXR-80

Order No. 0200080



8-channel audio mixer, with integrated MP3 player and Bluetooth receiver.

- Integrated USB audio interface (will be identified and addressed as an external sound card)
- Full-duplex USB port (allows for simultaneous recording and reproduction) for reproduction of digital audio data from a PC and for recording mixings onto a PC
- 6 mono input channels with gain control, 3-way equalizer and pan pot
- 1 stereo input channel with 3-way equalizer and balance control
- MP3 player
- USB interface
- Bluetooth receiver
- DSP delay, adjustable
- Adjustable aux return input and FX send output
- Tape record/play connections
- 5-band stereo graphic equalizer
- +48 V phantom power, can be activated as required
- Pre-fader listening (PFL) to the stereo input channels via adjustable headphone output
- Stereo LED level display



Model	MXR-80
Mic input	2.2 mV, bal. 8 x XLR
Line input	50 mV (stereo), 1 x 6.3 mm jack L/R 30 mV (mono), 8 x 6.3 mm jack
Tape (play)	290 mV, 1 x RCA L/R
Aux input	420 mV, 1 x 6.3 mm jack L/R
Master output	880 mV, bal. 1 x XLR L/R 880 mV, 1 x 6.3 mm jack L/R
Effect send	9 V, 1 x 6.3 mm jack
Tape (rec)	400 mV, 1 x RCA L/R
Headphones	≥ 8 Ω, 1 x 6.3 mm jack
Frequency range	20-20,000 Hz
THD	< 0.03%
S/N ratio	> 82 dBA
Equalizer bass	±15 dB/80 Hz
Equalizer midrange	±15 dB/2.5 kHz
Equalizer treble	±15 dB/12 kHz
Power supply	~ 230 V/50 Hz/25 VA
Dimensions	382 x 53 x 340 mm
Weight	3.4 kg

MXR-60

Order No. 0200630



6-channel audio mixer, with integrated MP3 player and Bluetooth receiver.

- Integrated USB audio interface (will be identified and addressed as an external sound card)
- Full-duplex USB port (allows for simultaneous recording and reproduction) for reproduction of digital audio data from a PC and for recording mixings onto a PC
- 4 mono input channels with gain control, 3-way equalizer and pan pot
- 1 stereo input channel with 3-way equalizer and balance control
- MP3 player
- USB interface
- Bluetooth receiver
- DSP delay, adjustable
- Adjustable aux return input and FX send output
- Tape record/play connections
- 5-band stereo graphic equalizer
- +48 V phantom power, can be activated as required
- Pre-fader listening (PFL) to the stereo input channels via adjustable headphone output
- Stereo LED level display



Model	MXR-60
Mic input	2.2 mV, bal. 4 x XLR
Line input	50 mV (stereo), 1 x 6.3 mm jack L/R 30 mV (mono), 4 x 6.3 mm jack
Tape (play)	290 mV, 1 x RCA L/R
Aux input	420 mV, 1 x 6.3 mm jack L/R
Master output	880 mV, bal. 1 x XLR L/R 880 mV, 1 x 6.3 mm jack L/R
Effect send	9 V, 1 x 6.3 mm jack
Tape (rec)	400 mV, 1 x RCA L/R
Headphones	≥ 8 Ω, 1 x 6.3 mm jack
Frequency range	20-20,000 Hz
THD	< 0.03%
S/N ratio	> 82 dBA
Equalizer bass	±15 dB/80 Hz
Equalizer midrange	±15 dB/2.5 kHz
Equalizer treble	±15 dB/12 kHz
Power supply	~ 230 V/50 Hz/20 VA
Dimensions	324 x 53 x 340 mm
Weight	2.9 kg