

MXR-6

Order No. 0200280



6-channel audio mixer, with DSP effect unit, integrated MP3 player and Bluetooth receiver.

- Integrated USB audio interface (will be identified and addressed as an external sound card)
- Full-duplex USB port (allows for simultaneous recording and reproduction) for reproduction of digital audio data from a PC and for recording mixings onto a PC
- 4 mono input channels with gain control, 2-way equalizer and pan pot
- 2 stereo input channels with 2-way equalizer and balance control
- MP3 player
- USB interface
- Bluetooth receiver
- 16 adjustable DSP effects
- Adjustable aux return input and FX send output
- +48 V phantom power, can be activated as required
- Adjustable headphone output
- Stereo LED level display
- Power is provided via USB or enclosed power supply



| Model | MXR-6 |
|------------------|---|
| Mic input | 2 mV, bal. 4 x XLR |
| Line input | 100 mV (stereo), 2 x 6.3 mm jack L/R 60 mV (mono), 2 x 6.3 mm jack |
| Aux input | 400 mV, 1 x 6.3 mm jack L/R |
| Master output | 500 mV, 1 x 6.3 mm jack L/R |
| Effect send | 4.4 V, 1 x 6.3 mm jack |
| Headphones | ≥ 8 Ω, 1 x 6.3 mm jack |
| Frequency range | 20-20,000 Hz |
| THD | < 0.03% |
| S/N ratio | > 83 dBA |
| Equalizer bass | ±15 dB/80 Hz |
| Equalizer treble | ±15 dB/12 kHz |
| Power supply | USB or encl. power supply |
| Dimensions | 308 x 53 x 205 mm |
| Weight | 1.9 kg |

MXR-4

Order No. 0200250



4-channel audio mixer, with DSP effect unit, integrated MP3 player and Bluetooth receiver.

- Integrated USB audio interface (will be identified and addressed as an external sound card)
- Full-duplex USB port (allows for simultaneous recording and reproduction) for reproduction of digital audio data from a PC and for recording mixings onto a PC
- 2 mono input channels with gain control, 2-way equalizer and pan pot
- 1 stereo input channel with 2-way equalizer and balance control
- MP3 player
- USB interface
- Bluetooth receiver
- 16 adjustable DSP effects
- Adjustable aux return input and FX send output
- +48 V phantom power, can be activated as required
- Adjustable headphone output
- Stereo LED level display
- Power is provided via USB or supplied power supply



| Model | MXR-4 |
|------------------|---|
| Mic input | 2 mV, bal. 2 x XLR |
| Line input | 100 mV (stereo), 2 x 6.3 mm jack L/R 60 mV (mono), 2 x 6.3 mm jack |
| Aux input | 400 mV, 1 x 6.3 mm jack L/R |
| Master output | 500 mV, 1 x 6.3 mm jack L/R |
| Effect send | 4.4 V, 1 x 6.3 mm jack |
| Headphones | ≥ 8 Ω, 1 x 6.3 mm jack |
| Frequency range | 20-20,000 Hz |
| THD | < 0.03% |
| S/N ratio | > 83 dBA |
| Equalizer bass | ±15 dB/80 Hz |
| Equalizer treble | ±15 dB/12 kHz |
| Power supply | USB or encl. power supply |
| Dimensions | 228 x 53 x 205 mm |
| Weight | 1.4 kg |