



LTR-102

Order No.: 0241800

PRODUCTINFOS

Line Transformers

For an optimum signal transmission from line units to a mixer or amplifier. By using a transformer coupling, interferences due to matching problems, e.g. hum loops, are prevented to a large extent. Input and output are galvanically isolated.

All inputs and outputs can be used via 6.3 mm jacks and XLR jacks, balanced as well as unbalanced.

Line transformer

- Balanced and unbalanced inputs and outputs
- Output impedance can be switched from 1:1/600 Ω to 2:1/150 Ω
- Phase can be switched from 0° to 180°
- Ground lift switch
- Wideband balancing transformer
- Robust metal housing

Production Partner 03/2013

“Attractively-priced line transformer. The LTR-102 is of neat workmanship and provides respectable

measured values.”

Manufacturer information:

MONACOR INTERNATIONAL GmbH & Co. KG
Zum Falsch 36
28307 Bremen
Germany
info@monacor.com

Safety Notes and Warning Messages

The unit is suitable for indoor use only. Protect it against dripping water and splash water, high air humidity and heat (admissible ambient temperature range: 0 - 40 °C).

If the unit is to be put out of operation permanently, take it to a local recycling plant for a disposal which is not harmful to the environment.

TECHNICAL SPECIFICATIONS

LTR-102

Description	line transformer
Frequency range	20-25,000 Hz
Input signal	5 V
Input impedance	600 Ω
Output impedance	600 Ω/150 Ω
Transmission ratio	1:1/2:1
Admiss. ambient temp.	0-40 °C
Dimensions	120 x 44 x 90 mm
Weight	545 g
Inputs	1 x 6.3 mm jack, bal. 1 x XLR, bal.
Outputs	1 x 6.3 mm jack, bal. 1 x XLR, bal.
Other features	Optimum load imped.: $\geq 2 \text{ k}\Omega$ Optimum source imped.: 50-600 Ω

LTR-102

EAN code	4007754164886
Net weight	0.545 kg