



## MXR-80

Order No.: 0200080

### PRODUCTINFOS

#### **8-channel audio mixer,**

with integrated MP3 player and Bluetooth receiver.

- Integrated USB audio interface (will be identified and addressed as an external sound card)
- Full-duplex USB port (allows for simultaneous recording and reproduction) for reproduction of digital audio data from a PC and for recording mixings onto a PC
- 6 mono input channels with gain control, 3-way equalizer and pan pot
- 1 stereo input channel with 3-way equalizer and balance control
- MP3 player
- USB port
- Bluetooth receiver
- DSP delay, adjustable
- Adjustable aux return input and FX send output
- Tape record/play connections
- 5-band stereo graphic equalizer
- +48 V phantom power, can be activated as required
- Pre-fader listening (PFL) to the stereo input channels via adjustable headphone output
- Stereo LED level display

## TECHNICAL SPECIFICATIONS

### MXR-80

Input channels	8
Number of mix/mono	6
No. of stereo	1
Mic input	2.2 mV, bal. 8 x XLR
Line input	50 mV (stereo), 1 x 6.3 mm jack L/R 30 mV (mono), 8 x 6.3 mm jack
Tape (play)	290 mV, 1 x RCA L/R
Aux input	420 mV, 1 x 6.3 mm jack L/R
Master output	880 mV, bal. 1 x XLR L/R 880 mV, 1 x 6.3 mm jack L/R
Effect send	9 V, 1 x 6.3 mm jack
Tape (rec)	400 mV, 1 x RCA L/R
Headphones	≥ 8 Ω, 1 x 6.3 mm jack
USB	yes
Bluetooth	yes
Frequency range	20-20,000 Hz
THD	< 0.03%
S/N ratio	> 82 dB(A)
Equalizer bass	±15 dB/80 Hz
Equalizer midrange	±15 dB/2.5 kHz
Equalizer treble	±15 dB/12 kHz
equalizer	5-band equalizer
Phantom power	+48 V
Power supply	~ 230 V/50 Hz/25 VA
Mains voltage	~ 230 V
Mains frequency	50 Hz
Power consumption, operation	25 VA
Admiss. ambient temp.	0-40 °C
Width	382 mm
Height	53 mm
Depth	340 mm
Weight	3.4 kg
Packing dimensions (W x H x L)	0.43 x 0.41 x 0.09 m
Gross weight	3.89 kg
Net weight	3.42 kg

