

Tender text

DELTA-160R

16-channel digital audio mixer

- 12 mono input channels (8 XLR inputs, 4 comb. inputs XLR/6.3 mm jack)
- 2 stereo input channels
- 1 S/PDIF input
- 1 USB audio channel
- USB recording (stereo master) and playback with 192 kHz/24 bits max.
- Integrated DSP (2 x reverb, 2 x modulation, 2 x delay, 2 x 31-band graphic equalizer)
- 8 XLR outputs
- 1 AES/EBU output
- 1 S/PDIF output
- Can be remote-controlled via app (iOS)
- +48 V phantom power, can be activated as required for each mono input channel
- 1 adjustable headphone output
- 17.8 cm (7") colour LCD touch screen for display and settings
- 482 mm (19") rack installation, 4 RS

Specifications:

No. of channels	16
No. of inputs	20
Mic input	0.4 mV, bal. (XLR), 0.4 mV/3 mV, bal. (comb. jack)
Line input	8 mV, bal. (stereo)
Master output	700 mV, bal. (XLR)
Headphones	> 8 Ω
WiFi	yes, via USB Wi-Fi Dongle
USB	yes
Frequency range	20-20,000 Hz
THD	< 0.01%
Crosstalk	> 69 dB
Equalizer bass	DSP (4-band equalizer)
Equalizer midrange	DSP (4-band equalizer)
Equalizer treble	DSP (4-band equalizer)
equalizer	DSP (15-band equalizer)
Phantom power	+48 V
Power supply	~ 100-240 V/50-60 Hz/45 VA
Mains voltage	~ 100-240 V
Mains frequency	50-60 Hz
Power consumption, operation	45 VA
Admiss. ambient temp.	0-40 °C
Width	482 mm
Height	180 mm
Depth	155 mm
Rack spaces, RS	4 RS

Weight

4.62 kg

Brand: IMG STAGELINE

Type: DELTA-160R

Quantity: 1

Packing dimensions (W x H x L): 0.58 x 0.29 x 0.26 m

Gross weight: 5.72 kg

Net weight: 4.62 kg

Item weight (w/o accessories): 4.62 kg