



DELTA-160R

Order No. 0203180



16-channel digital audio mixer

- 12 mono input channels (8 XLR inputs, 4 comb. inputs XLR/6.3 mm jack)
- 2 stereo input channels
- 1 S/PDIF input
- 1 USB audio channel
- USB recording (stereo master) and playback with 192 kHz/24 bits max.
- Integrated DSP (2 x reverb, 2 x modulation, 2 x delay, 2 x 31-band graphic equalizer)
- 8 XLR outputs
- 1 AES/EBU output
- 1 S/PDIF output
- Can be remote-controlled via app (iOS)
- +48 V phantom power, can be activated as required for each mono input channel
- 1 adjustable headphone output
- 17.8 cm (7") colour LCD touch screen for display and settings
- 482 mm (19") rack installation, 4 RS



Model	DELTA-160R
Mic input	0.4 mV, bal. (XLR), 0.4 mV/3 mV, bal. (comb. jack)
Line input	8 mV, bal. (stereo)
Master output	700 mV, bal. (XLR)
Headphones	> 8 Ω
Frequency range	20-20,000 Hz
THD	< 0.01%
Crosstalk	> 69 dB
Equalizer bass	DSP (4-band equalizer)
Equalizer midrange	DSP (4-band equalizer)
Equalizer treble	DSP (4-band equalizer)
Power supply	~ 100-240 V/50-60 Hz/45 VA
Dimensions	482 x 180 x 155 mm
Weight	4.62 kg

