

Tender text

MPX-1/BK

Stereo DJ mixer

- 2 stereo input channels, each with gain control and 2-way equalizer, switchable phono/line
- DJ microphone channel with talkover, manually selectable
- Pre-fader listening (PFL) to the stereo input channels via adjustable headphone output
- Replaceable crossfader for crossfading between the two input channels
- Particularly easy-sliding high-quality faders with additional guides
- Stereo LED level display

Specifications:

No. of channels	2
No. of inputs	4
Mic input	1.5 mV, 49 dB, 1 x 6.3 mm jack
Line input	150 mV, 61 dB, 2 x RCA L/R
Phono input	3 mV, 2 x RCA L/R
Master output	1 V/600 Ω , 1 x RCA L/R
Record output	0.5 V/600 Ω , 1 x RCA L/R
Headphones	$\geq 8 \Omega$, 1 x 6.3 mm jack
Bluetooth	
Frequency range	20-20,000 Hz
THD	0.1%
Equalizer bass	± 12 dB/50 Hz
Equalizer treble	± 12 dB/10 kHz
Talkover	-16 dB
Crossfader	yes
Power supply	via encl. plug-in power supply
Admiss. ambient temp.	0-40 °C
Width	164 mm
Height	218 mm
Depth	77 mm
Weight	1.2 kg

Brand: IMG STAGELINE

Type: MPX-1/BK

Quantity: 1

Packing dimensions (W x H x L): 0.24 x 0.11 x 0.31 m

Gross weight: 2.165 kg

Net weight: 1.49 kg

Item weight (w/o accessories): 1.2 kg