

Tender text

MPX-206/SW

6-channel stereo mixer

- 4 stereo input channels, each with separate LED level display, switchable line/phono (channels 1-2) and line/line (channels 3-4), gain control, 3-way equalizer with cut function
- 1 DJ microphone channel with switchable automatic talkover and 1 guest microphone channel, both channels with gain control as well as 2-way tone control
- 1 stereo effect way (send/return)
- 2 master outputs, each with beat LED and 1 booth output
- 1 record output
- LED level display, switchable between both master outputs
- Crossfader with assignment switches for channels 1-4 and cut switch function to suppress high frequencies, midrange and bass frequencies
- Adjustable headphone output
- Fader start for the stereo inputs (channels 1-4)
- Connection for gooseneck light GNL-404

Specifications:

No. of channels	6
No. of inputs	12
Mic input	1.5 mV, 2 x 6.3 mm jack
Line input	150 mV, 3 x RCA L/R
CD input	150 mV, 3 x RCA L/R
Phono input	3 mV, 2 x RCA L/R
Effect return	135 mV, 1 x RCA L/R
Master output	1 V/600 Ω , 1 x 3-pole XLR L/R
Record output	300 mV/600 Ω , 1 x RCA L/R
Monitor output	1 V/600 Ω , 1 x RCA L/R
Effect send	300 mV/600 Ω , 1 x RCA L/R
Headphones	$\geq 8 \Omega$, 6.3 mm jack
Gooseneck lamp	12 V/5 W, 4-pole XLR
Bluetooth	
Frequency range	20-20,000 Hz
THD	0.05%
S/N ratio	> 50 dB
Equalizer bass	+15 dB, -30 dB/50 Hz
Equalizer midrange	+15 dB, -30 dB/1 kHz
Equalizer treble	+15 dB, -30 dB/10 kHz
Talkover	-12 dB, switchable
Crossfader	yes
Power supply	~ 230 V/50 Hz/14 VA
Mains voltage	~ 230 V
Mains frequency	50 Hz
Power consumption, operation	14 VA

Admiss. ambient temp.	0-40 °C
Width	482 mm
Height	266 mm
Depth	110 mm
Rack spaces, RS	6
Weight	6.48 kg

Brand: IMG STAGELINE

Type: MPX-206/SW

Quantity: 1

Packing dimensions (W x H x L): 0.305 x 0.16 x 0.56 m

Gross weight: 7.82 kg

Net weight: 6.48 kg

Item weight (w/o accessories): 6.48 kg