



LC-31

Order No.: 0251670

PRODUCTINFOS

2-channel 2-way line combiner,

(4 inputs/2 outputs), e.g. for connecting 2 mixers to one amplifier.

- 1 galvanically isolated, balanced XLR input (600 Ω) with ground lift switch for each channel
- 1 balanced XLR direct input for each channel
- 1 balanced XLR output (600 Ω) for each channel
- Frequency range: 20-20,000 Hz
- Robust metal housing with very good shielding qualities, suitable for stage applications
- Dimensions: 160 x 55 x 85 mm
- Weight: 761 g

SOUNDCHECK 07/2007

on the FGA-102, FGA-202, LC-31, MC-31 and LSP-102:

“Every musician or sound engineer should have these little helpers in their toolbox. They impress by their unobtrusiveness. Both the robust metal housing and the functionality of these transformers allow to solve many problems on stage or in the studio at a reasonable price.”

tools4music 06/2009

on the LSP-102, LC-31, FGA-102, FGA-202, DIB-102

"Recommendable and fit for on-the-road applications. An attractively priced little audio aid, perfect for the 'ever accompanying' tool case."

TECHNICAL SPECIFICATIONS

LC-31

Description	combiner
Frequency range	20-20,000 Hz
Input impedance	600 Ω
Output impedance	600 Ω
Admiss. ambient temp.	0-40 °C
Dimensions	160 x 55 x 85 mm
Weight	761 g
Inputs	4 x XLR, bal.
Outputs	2 x XLR, bal.
Other features	ground lift switch