



MPR-6

Order No.: 0210680

PRODUCTINFOS

Microphone preamplifier,

for connecting up to 2 microphones to one line input.

- Stereo or 2 x mono
- Wide frequency range
- Black metal case
- Supplied with plug-in power supply

Microphone preamplifier,

for connecting up to 2 microphones to a line input of a hi-fi system, an amplifier or a mixer.

- Stereo or 2 x mono
- Wide frequency range
- Black metal case
- Supplied with plug-in power supply

Manufacturer information:

MONACOR INTERNATIONAL GmbH & Co. KG
Zum Falsch 36
28307 Bremen
Germany
info@monacor.com

TECHNICAL SPECIFICATIONS

MPR-6

Description	microphone preamplifier
Frequency range	5-40,000 Hz
Input signal	2 mV/1 V output
Input impedance	10 k Ω
Output signal	max. 3.2 V/47 k Ω
Gain	53 dB
S/N ratio	63 dB
THD	0.05%
Admiss. ambient temp.	0-40 °C
Power supply	via encl. plug-in power supply
Dimensions	67 x 37 x 121 mm
Weight	215 g
Inputs	2 x 6.3mm jack
Outputs	2 x RCA

MPR-6

EAN code	4007754121001
Net weight	0.275 kg