



## FLY-16R

Order No.: 0259570

**Price upon request**

### PRODUCTINFOS

#### **16-channel wireless PA audio receiver,**

with UHF PLL technology.

- For analogue wireless transmission of line audio signals in PA systems
- Frequency range: 823-832 MHz
- 16 pre-programmed channels, selectable
- Up to 8 intermodulation-free channels
- Audio transmission range: 30-17,000 Hz
- Multiple receivers FLY-16R can be operated via one transmitter FLY-16T
- Indication for channel and battery status
- 3-pole XLR jack
- Power supply via 1 x 1.5 V battery AA size (not supplied) or micro USB jack (5 V/150 mA)
- Supplied with USB cable
- Dimensions: 22 x 23 x 102 mm

**There are restrictions or requirements within the EU!**

**Please read the notes regarding wireless systems in the section "IMPORTANT INFORMATION"!**

### **tools4music 01/2019**

“An elegant solution for an irritating problem. Both time advantage and benefits for practical application are huge, especially when controlling the delay lines or for multi-room applications.”

### **delamar.de**

“Simple transmission path for line signals. The FLY-16SET from IMG STAGELINE is a very compact, lightweight and easy-to-use wireless system for line signals which provides a perfect sound. The operation is licence-free in the EU. During our tests, the wireless connection has always been reliable and interference-free. The power is provided either via standard batteries AA size or via the supplied micro USB cable.”

### **SOUNDCHECK 02/2019**

“Wireless system for audio line signals which is suitable for general applications. The signal quality absolutely meets professional requirements and can also be used for the transmission of master signals.”

### **OKEY 148**

**“Sometimes, it is the little things that make a musician's life a lot easier. During the test, the FLY-16 has really become one of our favourites. It is both practical and reliable [...] highly convenient systems. Even our active mobile phones did not interfere with the signal paths.”**

## **TECHNICAL SPECIFICATIONS**

### **FLY-16R**

#### General information

Description 16-channel wireless PA audio receiver

Carrier frequency range 823-832 MHz

Audio frequency range 30-17,000 Hz

Channels 16

THD 0.3%

Admiss. ambient temp. 0-40 °C

#### Specifications receiver

Power supply receiver 1 x 1.5 V batt. AA size,  
DC 5 V/150 mA via micro USB jack

Width receiver 22 mm

Height receiver 23 mm

Depth receiver 102 mm

Weight receiver 25 g

Connections receiver 3-pole XLR plug

