



G-7SET

Order No.: 0250760

PRODUCTINFOS

Pair of professional dual-band transceivers,

case set,

consisting of 2 transceivers with belt clip, 2 clip-on mics with earphones, charger for 2 transceivers, 2 rech. battery packs.

- 8 PMR channels 446 MHz
- 69 LPD channels 433 MHz
- Boost function for a wide operating range
- High-performance rech. batteries for high operational availability
- Manual transmit mode (PTT) or hands-free voice-activated transmit mode (VOX)
- Monitoring function
- Automatic squelch
- Channel scan mode (SCAN)
- CTCSS tones
- Dual watch
- Vibracall function
- Key lock
- Backlit LCD
- Supplied in a robust hard-sided case

Licence-free, please refer to instruction manual on the MONACOR website.

TECHNICAL SPECIFICATIONS

G-7SET

General information

Description	hand-held transceiver set
Carrier frequency range	446.00625-446.09375 MHz (PMR) 433.075-434.775 MHz (LPD)
Channels	8 PMR, 69 LPD
Admiss. ambient temp.	-20 °C to +55 °C
Power supply	4 x rech. battery AA size, 800 mAh
Dimensions	58 x 195 x 34 mm
Total weight	1.203 kg
Connections	2.5 mm jack (microphone) 3.5 mm jack (speaker)
Specifications transmitter	
Transmitting power	500 mW
Operating range	≤ 5,000 m