



MMX-602/SW

Order No.: 0202230

PRODUCTINFOS

Microphone line mixer,

6 channels.

- 6 stereo line inputs, 6 balanced mono microphone inputs, switchable
- Adjustable automatic talkover (-12 dB), switchable for channel 1 or channels 1+2
- Balance control for each stereo input channel
- 3-way equalizer
- 12 V phantom power can be activated as required
- LED VU meter, peak LED
- Master output and record output
- Output can be switched stereo/mono
- Adjustable headphone output
- 482 mm (19") rack installation, 1 RU

Manufacturer information:

MONACOR INTERNATIONAL GmbH & Co. KG
Zum Falsch 36
28307 Bremen
Germany
info@monacor.com

TECHNICAL SPECIFICATIONS

MMX-602/SW

Input channels	6
Number of mix/mono	6
No. of stereo	6
Mic input	1 mV/6.6 k Ω , 6 x 3-pole XLR, bal.
Line input	100 mV/10 k Ω , 6 x RCA L/R
Master output	1 V/600 Ω , 1 x RCA L/R 1 x 3-pole XLR L/R, bal.
Record output	310 mV/600 Ω , 1 x RCA L/R
Headphones	> 8 Ω , 1 x 6.3 mm jack
Frequency range	20-20,000 Hz
THD	0.1%
S/N ratio	62 dB, unweighted
Equalizer bass	\pm 12 dB/50 Hz
Equalizer midrange	\pm 12 dB/1 kHz
Equalizer treble	\pm 12 dB/10 kHz
Talkover	-12 dB, manual
Power supply	~ 230 V/50 Hz/12 VA
Mains voltage	~ 230 V
Mains frequency	50 Hz
Power consumption, operation	12 VA
Admiss. ambient temp.	0-40 $^{\circ}$ C
Dimensions	482 x 47 x 208 mm, 1 RS
Width	482 mm
Height	47 mm
Depth	208 mm
Rack units, RU	1
Weight	2.8 kg
Packaging dimensions (W x H x L)	0.25 x 0.09 x 0.53 m
Gross weight	3.76 kg
Net weight	2.985 kg

MMX-602/SW

EAN code	4007754182736
Net weight	2.985 kg