



MXR-4

Order No.: 0200250

PRODUCTINFOS

4-channel audio mixer,

with DSP effect unit, integrated MP3 player and Bluetooth receiver.

- Integrated USB audio interface (will be identified and addressed as an external sound card)
- Full-duplex USB port (allows for simultaneous recording and reproduction) for reproduction of digital audio data from a PC and for recording mixings onto a PC
- 2 mono input channels with gain control, 2-way equalizer and pan pot
- 1 stereo input channel with 2-way equalizer and balance control
- MP3 player
- USB port
- Bluetooth receiver
- 16 adjustable delay effects
- Adjustable aux return input and FX send output
- +48 V phantom power, can be activated as required
- Adjustable headphone output
- Stereo LED level display
- Power is provided via USB or supplied power supply

Manufacturer information:

MONACOR INTERNATIONAL GmbH & Co. KG
Zum Falsch 36
28307 Bremen
Germany
info@monacor.com

TECHNICAL SPECIFICATIONS

MXR-4

Input channels	4
Number of mix/mono	2
No. of stereo	1
Mic input	2 mV, bal. 2 x XLR
Line input	100 mV (stereo), 2 x 6.3 mm jack L/R 60 mV (mono), 2 x 6.3 mm jack
Aux input	400 mV, 1 x 6.3 mm jack L/R
Master output	500 mV, 1 x 6.3 mm jack L/R
Effect send	4.4 V, 1 x 6.3 mm jack
Headphones	$\geq 8 \Omega$, 1 x 6.3 mm jack
USB	yes
Bluetooth	yes
Frequency range	20-20,000 Hz
THD	< 0.03%
S/N ratio	> 83 dB(A)
Equalizer bass	± 15 dB/80 Hz
Equalizer treble	± 15 dB/12 kHz
Phantom power	+48 V
Power supply	USB or encl. power supply
Admiss. ambient temp.	0-40 °C
Dimensions	228 x 53 x 205 mm
Width	228 mm
Height	53 mm
Depth	205 mm
Weight	1.4 kg
Packaging dimensions (W x H x L)	0.255 x 0.24 x 0.08 m
Gross weight	1.625 kg
Net weight	1.48 kg

MXR-4

EAN code

4007754273366

Net weight

1.48 kg