



LC-324DMX

Order No.: 0387720

PRODUCTINFOS

LED DMX controller,

for controlling all standard 3-channel to 8-channel LED spotlights.

- Operation with up to 4 LED spotlights, to be controlled individually or in combination
- Up to 8 DMX channels for each spotlight
- DMX channels for red, green, blue, white, master and strobe
- Channel sequence for red, green, blue, white, master and strobe can be patched
- 3 to 8 DMX channels can be selected for each spotlight
- Manual control via 6 faders
- Colour assignment directly via button for the colours: red, light red, orange, yellow, green, light green, cyan, white, blue, light blue, pink and purple
- 4 automatic programs
- Audio control via built-in microphone
- Buttons for blackout, full-on, fader and music control
- LED indication for each button
- Robust metal console housing
- Connections: 1 x 3-pole XLR (DMX out), 1 x low-voltage jack
- Power is provided via enclosed plug-in power supply
- Dimensions: 242 x 156 x 62 mm
- Weight: 1.25 kg

tastenwelt 05/2017

“One of the most straightforward light control units for stage applications.”

TECHNICAL SPECIFICATIONS

LC-324DMX

Description	LED DMX controller
DMX interface	DMX512
No. of DMX channels	32
No. of DMX outputs	1
No. of channel faders	6
No. of devices	4
Blackout function	yes
Music-controlled	yes
Suitable for	3-channel to 8-channel LED spotlights
Power supply	encl. plug-in power supply
Dimensions	242 x 156 x 62 mm
Width	242 mm
Height	156 mm
Depth	62 mm
Admiss. ambient temp.	0-40 °C
Weight	1.25 kg
Connections	1 x 3-pole XLR (DMX out)