



## TXS-900HSE

Order No.: 0255250

## **PRODUCTINFOS**

## Multifrequency pocket transmitter,

with UHF PLL technology.

- 2 frequency ranges
- SYNC function for synchronisation with receivers TXS-900 and TXS-920
- Mute function
- Sensitivity can be adjusted in 3 steps
- LCD for indicating channel and battery status
- Suitable for combination with headband/earband microphones and tie clip microphones with 3-pole mini XLR connector
- Belt clip
- Power supply via 2 x 1.5 V battery AA size (not supplied)

There are restrictions or requirements within the EU! Please read the notes regarding wireless systems in the section "IMPORTANT INFORMATION"!



## **TECHNICAL SPECIFICATIONS**

| <b>TXS-900HS</b> | Е |
|------------------|---|
| 1/2 200112       |   |

| General information        |                           |
|----------------------------|---------------------------|
| Description                | pocket transmitter        |
| Carrier frequency range    | 823-832 MHz + 863-865 MHz |
| Audio frequency range      | 80-18,000 Hz              |
| Channels                   | 1                         |
| Operating time             | > 15 h                    |
| Admiss. ambient temp.      | 0-40 °C                   |
| Specifications transmitter |                           |
| Transmitting power         | 10 mW                     |
| Power supply transmitter   | 2 x 1.5 V batt. AA size   |
| Width transmitter          | 65 mm                     |
| Height transmitter         | 110 mm                    |
| Depth transmitter          | 25 mm                     |
| Weight transmitter         | 76 g                      |
| Connections transmitter    | 1 x 3-pole mini XLR       |
|                            |                           |