



MPX-1/BK

Order No.: 0202170

PRODUCTINFOS

Stereo DJ mixer

- 2 stereo input channels, each with gain control and 2-way equalizer, switchable phono/line
- DJ microphone channel with talkover, manually selectable
- Pre-fader listening (PFL) to the stereo input channels via adjustable headphone output
- Replaceable crossfader for crossfading between the two input channels
- Particularly easy-sliding high-quality faders with additional guides
- Stereo LED level display

TECHNICAL SPECIFICATIONS

MPX-1/BK

No. of channels	2
No. of inputs	4
Mic input	1.5 mV, 49 dB, 1 x 6.3 mm jack
Line input	150 mV, 61 dB, 2 x RCA L/R
Phono input	3 mV, 2 x RCA L/R

MPX-1/BK

Master output	1 V/600 Ω , 1 x RCA L/R
Record output	0.5 V/600 Ω , 1 x RCA L/R
Headphones	$\geq 8 \Omega$, 1 x 6.3 mm jack
Frequency range	20-20,000 Hz
THD	0.1%
Equalizer bass	± 12 dB/50 Hz
Equalizer treble	± 12 dB/10 kHz
Talkover	-16 dB
Crossfader	yes
Power supply	via encl. plug-in power supply
Admiss. ambient temp.	0-40 $^{\circ}\text{C}$
Width	164 mm
Height	218 mm
Depth	77 mm
Weight	1.2 kg